

READ & UNDERSTAND INSTRUCTIONS BEFORE PROCEEDING.

WARNING: FIRE HAZARD/ELECTRICAL HAZARD. THIS EQUIPMENT IS INTENDED TO BE INSTALLED ONLY BY QUALIFIED PERSONNEL. THE INSTALLATION MUST BE MADE IN ACCORDANCE WITH THE CURRENT EDITION OF THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE STATE AND LOCAL ELECTRICAL CODES. THE FINAL INSTALLATION MUST BE APPROVED BY THE APPROPRIATE, QUALIFIED ELECTRICAL/BUILDING INSPECTOR (S). IMPROPER INSTALLATION MAY RESULT IN A FIRE OR ELECTRICAL HAZARD.

INSTRUCTION SHEET
3SIS04-05
RECESSED HALL | STEP LIGHT

P/N: 3S-IS1005

1. ALWAYS DISCONNECT POWER BEFORE INSTALLATION AND/OR REMOVAL OF UNIT.
2. LOCATE AND MOUNT ELECTRICAL BOX IN SPECIFIED LOCATION IN ACCORDANCE WITH CURRENT ELECTRICAL CODES. SECURE ELECTRICAL BOX TO BLOCKING AS REQUIRED (BY OTHERS). NOTE: FACE OF MUD-RING PLATE MUST BE FLUSH WITH STUDS (MAX. 5/8" WALL THICKNESS).
3. INSURE THAT DRIVER INPUT VOLTAGE MATCHES POWER LINE VOLTAGE (E.G. 120V) WARNING!! DO NOT CONNECT LED TO DRIVER WHILE DRIVER IS ENERGIZED. DRIVER MUST BE LISTED FOR CLASS 2 OPERATION. MAX 350mA OUTPUT, CONSTANT CURRENT.
4. CONNECT INPUT POWER LINE WIRE TO BLUE POWER SUPPLY WIRE WITH WIRE NUT. CONNECT NEUTRAL POWER LINE WIRE TO BROWN POWER SUPPLY WIRE WITH WIRE NUT. GROUND ELECTRICAL BOX IN ACCORDANCE WITH LOCAL CODES.
5. PLACE POWER SUPPLY INTO ELECTRICAL BOX USING PROVIDED DOUBLE SIDED STICKY TAPE, THEN PROPERLY PLACE ALL WIRES (EXCEPT DRIVER OUTPUT WIRES) INTO ELECTRICAL BOX.
6. CONNECT DRIVER OUTPUT WIRES TO LED LUMINAIRE BLACK(-) TO BLACK(-), RED(+) TO RED(+) USING WIRE NUTS (PROVIDED) AS SHOWN. WARNING!! IMPROPER WIRING WILL DAMAGE LED.
7. INSERT WIRES INTO ELECTRICAL BOX AS YOU INSERT LED LUMINAIRE. MOUNT LED LUMINAIRE USING THE TWO MOUNTING SPRINGS. TO INSERT, ROTATE SPRINGS INWARD AND INTO MOUNTING HOLE. CONTINUE PUSHING LUMINAIRE INTO MOUNTING HOLE UNTIL SPRINGS PULL LUMINAIRE INTO FINAL MOUNTED POSITION. NOTE THAT THE TABS ON THE ELECTRICAL BOX MUD-RING WILL ALIGN WITH THE COOLING FINES ON THE BACK OF THE LED LUMINAIRE. LOCATE LUMINAIRE SO THAT EYELID IS HORIZONTAL TO THE FLOOR OR AS SPECIFIED.
8. TURN POWER ON TO FIXTURE.

